

ORDERING INFORMATION

SERIES	200									
PRESSURE	-30 inHg to 0 psig	30vac	-30 inHg to 200 psig	30/200	0 psig to 150 psig	150	0 psig to 2000 psig	2000	0 psia to 15 psia	15A
	-30 inHg to 15 psig	30/15	-30 inHg to 300 psig	30/300	0 psig to 200 psig	200	0 psig to 3000 psig	3000	0 psia to 30 psia	30A
	-30 inHg to 30 psig	30/30	0 psig to 5 psig	5	0 psig to 300 psig	300	0 psig to 4000 psig	4000	0 psia to 60 psia	60A
	-30 inHg to 45 psig	30/45	0 psig to 10 psig	10	0 psig to 500 psig	500	0 psig to 5000 psig	5000	0 psia to 100 psia	100A
	-30 inHg to 300 psia	300A	0 psig to 15 psig	15	0 psig to 600 psig	600	0 psig to 6000 psig	6000	0 psia to 150 psia	150A
	-30 inHg to 60 psig	30/60	0 psig to 30 psig	30	0 psig to 750 psig	750	0 psig to 7500 psig	7500	0 psia to 200 psia	200A
	-30 inHg to 100 psig	30/100	0 psig to 60 psig	60	0 psig to 1000 psig	1000	0 psig to 10000 psig	10000	0 psia to 300 psia	300A
	-30 inHg to 150 psig	30/150	0 psig to 100 psig	100	0 psig to 1500 psig	1500	0 psig to 15000 psig	15000		
	psig = Gauge Pressure		psia = Absolute Pressure		Other ranges available on special request					
ACCURACY	1 ±0.5 % Full Scale (Best Fit Straight Line)				2 ±0.25 % Full Scale (Best Fit Straight Line)					
OUTPUT SIGNALS	2 0 Vdc to 5 Vdc, 3-wire		3 1 Vdc to 5 Vdc, 3-wire		4 1 Vdc to 6 Vdc, 3-wire		5 0 Vdc to 10 Vdc, 3-wire		6 1 Vdc to 11 Vdc, 3-wire	
PROCESS CONNECTIONS	1 1/8 " NPT male		2 1/4 " NPT male		3 7/16 " -20 UNF #4 SAE J-514 male				4 1/8 " NPT female	
	9 7/16 " -20 UNF #4 SAE J-514 female				10 1/4 " BSP male					
ELECTRICAL CONNECTIONS	1 36 " cable (connected to option 7)				2 4-pin bendix		3 6-pin bendix		36 Integral cable 36"	
	6 1/2 " NPT conduit (with 36 " cable)				7 Mini-Hirschmann (DIN EN 175301-803 Form C)		25 M12 x 1 4-pin			
NOTE: 0 Vdc to 5 Vdc and 0 Vdc to 10 Vdc outputs are also available in 4-wire configurations for use with other electrical systems.										
OPTIONS	ORF Threaded Orifice									

Please consult your local NOSHOK Distributor or NOSHOK, Inc. for availability and delivery information.